

1 SV 92	Hit	C-Di	AM Tuning	7d	TO-92	BB 112, BB 130, BB 509, 1SV134...135, ++
1 SV 93	Hit	C-Di	AM Tuning	7d	TO-92	BB 112, BB 130, BB 509, 1SV134...135, ++
1 SV 94	Hit	C-Di	UHF Tuning	31a	DO-41	BB 105, BB 205, BB 305, BB 405, BB 505++
1 SV 95	Hit	C-Di	VHF Tuning	31a	DO-41	BB 105, BB 205, BB 305, BB 405, BB 505++
1 SV 96	Hit	C-Di	Dual	7c	TO-92	-
1 SV 97	Hit	C-Di	VHF Tuning	31a	DO-35	BB 105, BB 205, BB 305, BB 405, BB 505++
1 SV 98	Hit	C-Di	TV/FM Tuner-AFC	31a	DO-35	BB 119, 1SV50, 1SV114, 1SV125
1 SV 99	Tos	PIN-Di	Band-S, 50V, 0,05A, 0,3pF, 7Ω	7d	TO-92	-
1 SV 100	Tos	C-Di	AM Tuning	41d		BB 112, BB 130, BB 509, 1SV134...135, ++
1 SV 101	Tos	C-Di	VHF AFC, FM Tuner	41d		BA 125, BB 119, 1SV114, 1SV125
1 SV 102	Tos	C-Di	HiFi AM Tuning, 28/30V, 360...450/15...21pF(2/25V)	41d		BB 112, BB 130, BB 509, 1SV134...135, ++
1 SV 103	Tos	C-Di	Dual, FM Tuning	41j		BB 104, BB 204, BB 304, MV 104, 1SV109
1 SV 104	Njr	C-Di	Dual, FM Tuning	7e	TO-92	BB 104, BB 204, BB 304, MV 104, 1SV109
1 SV 109	Hit	C-Di	Dual, FM Tuning	7e	TO-92	BB 104, BB 204, BB 304, MV 104, 1SV55
1 SV 110	Hit	C-Di	VHF Tuning	31a	SOD-17	BB 105, BB 205, BB 305, BB 405, BB 505++
1 SV 111	Hit	C-Di	UHF Tuning	31a	SOD-17	BB 105, BB 205, BB 305, BB 405, BB 505++
1 SV 112	Hit	C-Di	VHF Tuning	31a	SOD-17	BB 105, BB 205, BB 305, BB 405, BB 505++
1 SV 113	Hit	C-Di	VHF Tuning	31a	SOD-17	BB 105, BB 205, BB 305, BB 405, BB 505++
1 SV 114	Hit	C-Di	TV/FM Tuner-AFC	31a	DO-35	BB 119, 1SV50, 1SV114, 1SV125
1 SV 115	Hit	C-Di	AM Tuning	7d	TO-92	BB 112, BB 130, BB 509, 1SV134...135, ++
1 SV 116	Hit	C-Di	AM Tuning	7d	TO-92	BB 112, BB 130, BB 509, 1SV134...135, ++
1 SV 118	Nec	C-Di	AM Tuning	7d	TO-92	BB 112, BB 130, BB 509, 1SV134...135, ++
1 SV 121	Hit	PIN-Di	HF Abschw./Attenuator, 100V, 0,1A, Uf<1,1V(50mA)	31a	SOD-17	-
1 SV 122	Nec	PIN-Di	30V, Uf<1V(50mA), 0,4pF, 0,8Ω(100MHz)	Koax	SOD-31	-
1 SV 123	Tos	C-Di	UHF Tuning	71a(4mm)	SOD-23	BB 105, BB 205, BB 305, BB 405, BB 505++
1 SV 124	Hit	C-Di	VHF Tuning	31a	SOD-17	BB 105, BB 205, BB 305, BB 405, BB 505++
1 SV 125	Hit	C-Di	VHF/UHF AFC	31a	DO-34	BA 125, BB 119, 1SV114
1 SV 126	Hit	C-Di	FM/VHF Tuning	31a	DO-34	BB 109, BB 143, BBY 30, MV 109, 1SV50, ++
1 SV 128	Tos	PIN-Di	SMD, VHF/UHF, AGC, 50V, 0,05A, 0,25pF	35p	SOT-23	-
1 SV 129	Njr	C-Di	AM Tuning	33a	(4x4x2mm)	BB 112, BB 130, BB 509, 1SV134...135, ++
1 SV 132	Hit	C-Di	UHF Tuning	31a	DO-34	BB 105, BB 205, BB 305, BB 405, BB 505++
1 SV 133	Hit	C-Di	VHF Tuning	31a	DO-34	BB 105, BB 205, BB 305, BB 405, BB 505++
1 SV 134	Hit	C-Di	AM Tuning	31a	SOD-17	BB 112, BB 130, BB 509, 1SV102, 1SV129++
1 SV 135	Hit	C-Di	AM Tuning	31a	SOD-17	BB 112, BB 130, BB 509, 1SV102, 1SV129++
1 SV 136	Hit	C-Di	VHF/UHF Tuning	31a	SOD-17	BB 105, BB 205, BB 305, BB 405, BB 505++
1 SV 145	Hit	C-Di	TV-Tuner, VHF/UHF AFC, 34V	31a	SOD-17	BB 119, 1SV114, 1SV125
1 SV 146	Hit	C-Di	TV-Tuner, VHF/UHF AFC, 34V	31a	=DO-34	BB 119, 1SV114, 1SV125
1 SV 147	Tos	C-Di	Dual, FM Tuning	41e		BB 104, BB 204, BB304, MV 104, 1SV109
1 SV 148	Rhm	C-Di	UHF Tuning	71a(4mm)	SOD-23	BB 105, BB 205, BB 305, BB 405, BB 505++
1 SV 149	Tos	C-Di	AM Tuning	41d		BB 509, MV 1401...1404, 1SV134...135, ++
1 SV 151	Hit	C-Di	FM/VHF Tuner-AFC	31a	DO-34	BB 119, 1SV114, 1SV125, 1SV145...146
1 SV 153(A)	Tos	C-Di	SMD, TV, VHF/UHF Tuning	71a(2,7mm)	SOD-123	BB 515, BB 721, BB 723, BB 729...731
1 SV 154	Hit	PIN-Di	HF S, 65V, 0,1A	31a	DO-34	-
1 SV 155	Hit	C-Di	VHF Tuning	31a	DO-34	BB 205, BB 305, BB 405, BB 505, 1SV124++
1 SV 156	Nec	PIN-Di	HF Att, 30V, 0,05A, <0,6pF(20V), <15Ω>1kΩ(100MHz)	31a	DO-35	-
1 SV 157	Nec	PIN-Di	HF Att, 50V, 0,05A, <0,9pF(20V), <7Ω>1kΩ(100MHz)	31a	DO-35	1SV196
1 SV 160	Tos	C-Di	SMD, FM AFC, 15V, 7...14pF(4V), <1,2Ω(4V/50MHz)	35c	SOT-23	-
1 SV 161	Tos	C-Di	SMD, CATV-Tuning	71a(2,7mm)	SOD-123	BB 721, BB 723, BB 729...731
1 SV 163	Nec	C-Di	VHF/UHF AFC, 30V, 2,5...3,4/11...17pF(10/2V), <0,7Ω	31a		BB 117, BB 417, MA 840
1 SV 164	Nec	C-Di	VHF/UHF Tuning, 30V, 2...2,3/11...12,7pF(25/3V), <0,7Ω	31a		BB 405, BB 501, BB 505, 1SV111, 1SV148++
1 SV 165	Nec	C-Di	VHF/UHF Tuning, 30V, 2...2,5/10,3...13pF(25/3V), <0,7Ω	31a		BB 405, BB 501, BB 505, 1SV111, 1SV148++
1 SV 166	Nec	C-Di	FM/VHF Tuning, 30V, 5...6/28...32,5pF(25/3V), <0,7Ω	31a		BB 109, BB 143, BBY 30, MV 109, 1SV50
1 SV 166(1)	Nec	C-Di	FM/VHF Tuning, 30V, 5...6/29...34pF(25/3V), <0,7Ω	31a		BB 109, BB 143, BBY 30, MV 109, 1SV50
1 SV 166 S	Nec	C-Di	VHF VCO, 30V, >14/23...36pF(25/3V), <0,5Ω	31a		-
1 SV 167	Nec	C-Di	VHF/CATV Tuning, 30V, 2,8...3,3/26...32pF(25/3V), <1Ω	31a		1SV191, 1SV209
1 SV 169	Nec	C-Di	VHF/UHF Tuning, 30V, 2,1...2,5/14...16,4pF(25/2V)	31a		BB 405, BB 501, BB 505, 1SV111, 1SV148++
1 SV 170	Nec	C-Di	VHF/UHF AFC, 30V, 13,7...17pF(2V), <0,6Ω	31a		BB 117, BB 417, MA 840
1 SV 172	Tos	C-Di	SMD, Dual, VHF/UHF Band, AGC	35t	SOT-23	-
1 SV 178	Hit	PIN-Di	Antenn.-S, 65V, 0,15A	31a	DO-35	-
1 SV 183	Nec	C-Di	UHF-Tuning, VCO, 28V, 0,6...0,7/2...4pF(20/2V)	31a	DO-35	1SV210
1 SV 184	Nec	C-Di	FM/VHF-Tuning, VCO, 15V, 4...6/40...50pF(10/2V)	31a	DO-35	BB 109, BB 143, BBY 30, MV 109, 1SV213
1 SV 186	Tos	C-Di	UHF/SHF Tuning, 30/35V, 3,3...4,5/0,6...8,2pF(2/25V)	71a(2,7mm)	=SOD-123	-
1 SV 187	Hit	PIN-Di	Antenn.-S, HF Att, 60V, 0,05A, <2,4pF(0V), <5,5Ω	31a	SOD-17	-
1 SV 188	Hit	C-Di	VHF/UHF Tuning	71a(2,7mm)	SOD-123	BB 721, BB 723, BB 729...731
1 SV 191	Nec	C-Di	VHF/CATV Tuning, 30V, 2,5...3/32...37pF(25/2V), <0,8Ω	31a		1SV167, 1SV209
1 SV 193	Hit	C-Di	VHF/UHF Tuning	71a(2,7mm)	SOD-123	BB 721, BB 723, BB 729...731
1 SV 194	Hit	C-Di	VHF Tuning	71a(2,7mm)	SOD-123	BB 419, BB 619...620
1 SV 196	Nec	PIN-Di	HF Att, 50V, 0,05A, <0,9pF(20V), <7Ω>1kΩ(100MHz)	31a		1SV157
1 SV 200	Hit	C-Di	VHF Tuning, 30V, 26,5pF(2V), 2,55pF(25V)	71a(2,7mm)	SOD-123	BB 419, BB 619...620
1 SV 202	Hit	C-Di	UHF Tuning	71a(2,7mm)	SOD-123	BB 721, BB 723, BB 729...731
1 SV 203	Hit	C-Di	VHF Tuning	71a(2,7mm)	SOD-123	BB 419, BB 619...620
1 SV 204	Tos	C-Di	VHF/UHF AFC, 30/35V, 10,5...16/3,3...5,7pF(2/10V)	71a(2,7mm)	=SOD-123	-
1 SV 205	Rhm	C-Di	Tuning, 35V, 14,36pF(2V), 2,15pF(25V)	71a(2,7mm)	SOD-123	BB 721, BB 723, BB 729...31, 1SV202
1 SV 207	Rhm	C-Di	VHF/UHF, 30V, >2,7/30...33pF(25/2V), <0,8Ω	31a		-
1 SV 209	Nec	C-Di	VHF/CATV Tuning, 30V, 2,6...3/26,6...32pF(25/2V)	31a		1SV167, 1SV191
1 SV 210	Nec	C-Di	VHF/UHF-Tuning, VCO, 28V, 0,6...0,8/3...4pF(20/2V)	31a		1SV183
1 SV 211	Tos	C-Di	UHF CATV-Tuning, 30/35V, 33...39/2,6...3,2pF(2/25V)	71a(2,7mm)	=SOD-123	-
1 SV 212	Tos	C-Di	UHF VCO, 15V, 14...16/5,5...6,5pF(2/10V), <0,4Ω(470M)	71a(2,7mm)	=SOD-123	-
1 SV 213	Nec	C-Di	FM/VHF-Tuning, VCO, 15V, 3,5...6/35...41pF(10/2V)	31a		BB 109, BB 143, BBY 30, MV 109, 1SV184
1 SV 214	Tos	C-Di	=1SV153A:	71a(1,7mm)	SOD-323	-
1 SV 215	Tos	C-Di	=1SV161:	71a(1,7mm)	SOD-323	-
1 SV 216	Tos	C-Di	=1SV204:	71a(1,7mm)	SOD-323	-
1 SV 217	Tos	C-Di	=1SV211:	71a(1,7mm)	SOD-323	-
1 SV 218	Nec	C-Di	VHF/CATV Tuning, 30V, 2,5...3/32...37pF(25/2V), <0,8Ω	71a		MA 335, MA 337, MA 338, MA 353
1 SV 219	Nec	C-Di	VHF/CATV Tun., 30V, 2,6...3/26,6...32pF(25/2V), <0,8Ω	71a		MA 335, MA 337, MA 338, MA 353
1 SV 220	Nec	C-Di	VHF/UHF Tuning, VCO, 30V, 2...2,5/9,5...14pF(25/2V)	71a		BB 515, BB 721, BB 723, MA 321, MA 334
1 SV 221	Nec	C-Di	VHF/UHF Tuning, VCO, 30V, 2...2,5/14...16,4pF(25/2V)	71a		BB 515, BB 721, BB 723, MA 321, MA 334
1 SV 222	Nec	C-Di	VHF/UHF Tuning, VCO, 30V, 5...6,3/13,7...17pF(10/2V)	71a		-
1 SV 223	Rhm	C-Di	=1SV205:	71a(1,7mm)	SOD-323	BB 535, BB 621...623, 1SV214
1 SV 224	Tos	C-Di	CATV Os, Converter	71a(2,7mm)	SOD-123	-
1 SV 225	Tos	C-Di	SMD, Dual, FM Tuning	35f	SOT-23	-
1 SV 226	Tos	C-Di	UHF CATV-Tuning	71a(2,7mm)	SOD-123	-
1 SV 227	Tos	C-Di	UHF CATV-Tuning	71a(2,7mm)	SOD-123	-