

2 SD 772 A	Si-N	=2SD772: 200/80V	17j	(BU 406)	17j
2 SD 772 B	Si-N	=2SD772: 250/80V	17j	(BU 406)	17j
2 SD 773	Si-N	NF, lo-sat, 20V, 2A, 1W, 110MHz	9b	2SC3225	7c(9mm)
2 SD 774	Si-N	Uni, 100V, 1A, 1W, 95MHz	9b	2SD774	9b
2 SD 776	Si-N	S-L, hi-beta, 200V, 5A, 100W, B>500	23a	-	-
2 SD 777	Si-N	TV-Reg, hi-beta, 55V, 4A, 100W, B>500	23a	-	-
2 SD 778	Si-N	Uni, 30V, 0,1A, 0,4W	9c	BC 546	7a
2 SD 779	Si-N	=2SD778: 60V	9c	BC 546	7a
2 SD 780	Si-N	SMD, Uni, 60V, 0,3A, 140MHz	35a	BC 817	35a
2 SD 781	Si-N	S-L, TV-HA, 150/60V, 2A	14h	-	-
2 SD 782	Si-N	TV-HA, 300/80V, 5A, 30W	17j	BU 406	17j
2 SD 783	Si-N	TV-HA, 1500/600V, 4A, 50W	23a	BU 208 A	23a
2 SD 784	Si-N	=2SD783: 1700/700V, 5A	23a	2SC3026	23a
2 SD 785	Si-N	=2SD783: 1900/700V, 5A	23a	(BU 209)	23a
2 SD 786(S)	Si-N	NF, ra, 50V, 0,3A, 0,25W, 100MHz	7c, 41c	BC 550	7a
2 SD 787	Si-N	NF-E, 20/16V, 2A, 0,9W, 100MHz	7c(9mm)	2SD1207	7c(9mm)
2 SD 788	Si-N	=2SD787: 20/20V	7c(9mm)	2SD1207	7c(9mm)
2 SD 789	Si-N	NF/E, 100/50V, 1A, 0,9W, 100MHz	7c(9mm)	2SD1812	7c(9mm)
2 SD 790	Si-N	=2SD789: 100/70V	7c(9mm)	2SD1812	7c(9mm)
2 SD 792	Si-N	TV-HA, 1500/700V, 5A, 35W(Tc=90°)	23a	BU 208 A	23a
2 SD 793	Si-N	NF/S-L, 40V, 3A, 10W, 65MHz	14h	2SD1348	14h
2 SD 794(A)	Si-N	NF/S-L, 70V, 3A, 10W, 60MHz	14h	(BD 189)	14h
2 SD 795(A)	Si-N	NF/HF-L, 50V, 3A, 20W, 95MHz	17j	2SC3258	17j
2 SD 796	Si-N-Darl	S-L, 500V, 8A, 100W, B>200, <1,4/21µs	23a	-	-
2 SD 797	Si-N	S-L, 100V, 30A, 200W, 3MHz, 1,5/7µs	23a	-	-
2 SD 798	Si-N-Darl	S-L, 600/300V, 6A, 30W, B>1500	17j	2SC798	17j
2 SD 799	Si-N-Darl+Di	S-L, 600/400V, 6A, 30W, B>600	17j	2SD798	17j
2 SD 800	Si-N	S-L, 750V, 4A, 30W, 8MHz	23a	BUW 11 A	18j
2 SD 801	Si-N	S-L, TV-SN, 800/375V, 6A, 50W	23a	BU 426 A	18j
2 SD 802	Si-N	=2SD801: 900/400V	23a	BU 426 A	18j
2 SD 803	Si-N-Darl+Di	NF/S-L, 120V, 8A, 100W, B>2000	23a	-	-
2 SD 804	Si-N	NF/S-L, 60V, 3A, 25W	17j	BD 243 C	17j
2 SD 807	Si-N	TV-HA, 1500/800V, 5A, 50W	23a	BU 208 A	23a
2 SD 808	Si-N	Uni, 25V, 0,5A, 0,4W, 250MHz	7c	BC 337	7a
2 SD 809(1)	Si-N	NF/S-L, lo-sat, 100V, 1A, 10W, 85MHz	14h	BD 139	14h
2 SD 810	Si-N	hi-beta, 20/20/20V, 4A, 30W, B=400	17j	-	-
2 SD 811	Si-N	S-L, 900/400V, 6A, 50W, 5MHz	23a	BU 426 A	18j
2 SD 812	Si-N	NF/S-L, 80V, 5A, 40W, 15MHz	17j	BD 243 C	17j
2 SD 813	Si-N	SMD, lo-sat, 25V, 0,5A, 150MHz	35a	(BC 817)	35a
2 SD 816	Si-N-Darl	S-L, 300V, 4A, 30W, B=1500, <2/20µs	17j	-	-
2 SD 817	Si-N	TV-HA, 1500/600V, 1,5A, 50W	23a	(BU 208 A)	23a
2 SD 818	Si-N	TV-HA, 1500/600V, 2,5A, 50W	23a	BU 208 A	23a
2 SD 819	Si-N	=2SD818: 3,5A	23a	BU 208	23a
2 SD 820	Si-N	=2SD818: 5A	23a	BU 208	23a
2 SD 821	Si-N	=2SD818: 6A	23a	BU 2508 A	18j
2 SD 822	Si-N	=2SD818: 7A	23a	BU 2508 A	18j
2 SD 823	Si-N	NF/S-L, TV-HA, 200/90V, 6A, 40W	17j	BU 406	17j
2 SD 824(A)	Si-N	NF/S-L, 120V, 6A, 60W, 10MHz	20j	2SC3264	20j
2 SD 825(A)	Si-N	NF/S-L, 120V, 7A, 80W, 10MHz	20j	2SC3264	20j
2 SD 826	Si-N	lo-sat, 60V, 5A, 10W, 120MHz	14h	-	-
2 SD 827	Si-N-Darl+Di	S-L, 500/500V, 4A, 50W, B>500	20j	-	-
2 SD 828	Si-N-Darl+Di	=2SD827: B=2000	20j	-	-
2 SD 829(K)	Si-N-Darl+Di	NF/S-L, 150/120V, 15A, 100W, B=4000	20j	-	-
2 SD 830	Si-N-Darl	NF/S-L, 150/100V, 5A, 30W, B>2000	17j	-	-
2 SD 833	Si-N-Darl	NF/S-L, 60V, 7A, 40W, B>4000	17j	-	-
2 SD 834	Si-N-Darl	S-L, 250/200V, 4A, 25W, B>1500	17j	-	-