

2 SK 54	N-FET	FM-V/M, 15V, Idss=0,8...5mA, Up<5,5V	9f, 7f	(BF 245)	7f
2 SK 55	N-FET	FM-V/M, 18V, Idss=3...14mA, Up<5,5V	9f, 7f	BF 245	7f
2 SK 61	N-FET	FM/VHF, 18V, Idss=1...10mA, Up<4V	7d	BF 245	7f
2 SK 68(A)	N-FET	NF, 50V, Idss=0,5...12mA, Up<1,5V	7a	-	
2 SK 83	N-FET	FM/VHF, 25V, Idss>0,5mA, Up<2,5V	7f	-	
2 SK 103	N-FET	NF/HF-V, 20V, Idss=0,02...1mA, Up<0,8V	-	-	
2 SK 104	N-FET	Uni, 30V, Idss=0,5...12mA, Up<4,5V	7f	-	
2 SK 105	N-FET	=2SK104: 50V	7a	-	
2 SK 107	N-FET	FM/VHF, 27V, Idss>2,7mA, Up<3,85V	7e	-	
2 SK 113	N-FET	Uni, 50V, Idss=5...150mA, Up<10V	2b(G-case)	-	
2 SK 117	N-FET	NF, ra, 50V, Idss>0,6mA, Up<1,5V	7a	-	
2 SK 121	N-FET	Uni, ra, 30V, Idss=0,9mA, Up<1,49V	7a, 7e	-	
2 SK 125	N-FET	FM/VHF, 25V, Idss>30mA, Up<6V	7e	-	
2 SK 127	N-FET	NF, ra, 50V, 20mA, Idss=0,5...12mA	7a	-	
2 SK 128	N-FET	NF, ra, 30V, 20mA, Idss>0,5mA, Up<1,5V	7a	-	
2 SK 132	MOS-N-FET-e	V-MOS, 100V, 7A, 100W, <1,7Ω, 18/14ns	23e	-	
2 SK 133	MOS-N-FET-e	=2SK132: 120V	23e	-	
2 SK 134	MOS-N-FET-e	=2SK132: 140V	23e	-	
2 SK 135	MOS-N-FET-e	=2SK132: 160V	23e	-	
2 SK 136	N-FET	Uni, ra, 20mA, 30V, Idss>0,5mA, Up<2V	7a	-	
2 SK 146	N-FET	=2SK147: Dual	7e + 7a	-	
2 SK 147	N-FET	Uni, ra, 40V, Idss>5mA, Up<1,2V	7a(9mm)	-	
2 SK 150	N-FET	Dual, 50V, Idss>1mA, Up<2V	7-SIP	-	
2 SK 161	N-FET	FM/VHF, 18V, Idss>1mA, Up<4V	41d	-	
2 SK 162	N-FET	Uni, ra, 40V, Idss>5mA, Up<1,2V	7a	-	
2 SK 163	N-FET	Uni, ra, 50V, Idss>1mA, Up<1,2V	7a	-	
2 SK 168	N-FET	FM-V/M/O, 30V, Idss>4mA, Up<3V	7f	-	
2 SK 170	N-FET	Uni, ra, 40V, Idss>1mA, Up<1,5V	7a	-	
2 SK 218	N-FET	Video-Camera, 15V, 50mA, Idss>5mA	7d	-	
2 SK 223	N-FET	NF-Tr, 80V, Idss>1,2mA, Up=0,75V	7e	-	
2 SK 300	N-FET	SMD, VHF, 15V, Idss>9,5mA, Up<2V	35f	-	
2 SK 301	N-FET	Uni, ra, 55V, ±30mA, Idss>0,5mA, Up<5V	7a	-	
2 SK 304	N-FET	Analog-S, 30V, Idss>0,6mA, Up<4V	40e	-	
2 SK 310	MOS-N-FET-e	V-MOS, 400V, 3A, 40W, <4Ω, 25/70ns	17p	BUK 455/600A,B	17p
2 SK 311	MOS-N-FET-e	=2SK310: 450V	17p	BUK 455/600A,B	17p
2 SK 315	N-FET	FM-V/M/O, 20V, Idss>2,5mA, Up<3,5V	40d	-	
2 SK 316	N-FET	SMD, Video-Camera, 10V, Idss>5mA, Up<3V	35f	-	
2 SK 319	MOS-N-FET-e	V-MOS, 400V, 5A, 50W, <1,83Ω, 50/120ns	17p	-	
2 SK 330	N-FET	Uni, 50V, Idss>1,2mA, Up<0,6V	41e	-	
2 SK 332	N-FET	Dual, 40V, 20mA, Idss>1,2mA, Up=0,5V	-	-	
2 SK 364	N-FET	Uni, 40V, Idss>2,6mA, Up<1,5V	7a	-	
2 SK 381	N-FET	Uni, 50V, Idss>0,3mA, Up<6V	41a	-	
2 SK 404	N-FET	Uni, ra, 20V, Idss>1,2mA, Up<2V	40e	-	
2 SK 405	MOS-N-FET-e	V-MOS-L, 160V, 8A, 100W, <1,4Ω(5A)	18p	-	
2 SK 413	MOS-N-FET-e	V-MOS, 140V, 8A, 100W, <0,5Ω, 50/110ns	18p	-	
2 SK 414	MOS-N-FET-e	=2SK413: 160V	18p	-	
2 SK 427	N-FET	AM-V/M/O, 15V, Idss>1,2mA, Up<1,5V	40e	-	
2 SK 502	MOS-N-FET-e	V-MOS-L, 400V, 3A, 40W, <4Ω, 35/15ns	17p	IRF 720	17p
2 SK 514	N-FET	Analog-S, 50V, 20mA, Idss>1mA, Up<4,5V	40a	-	
2 SK 515	N-FET	=2SK514: SMD	35f	-	
2 SK 534	MOS-N-FET-e	V-MOS, 800V, 5A, 100W, <4Ω, 75/220ns	18p	2SK727	18p
2 SK 544	MOS-N-FET-d	FM/VHF, 20V, 30mA, Idss>1,2mA, Up<2,5V	40e,d	-	
2 SK 552	MOS-N-FET-e*	V-MOS, 450V, 5A, 50W, <1,4Ω, 45/115ns	17p	BUK 455/600A,B	17p
2 SK 553	MOS-N-FET-e*	=2SK552: 500V	17p	BUK 455/600A,B	17p
2 SK 583	MOS-N-FET-e	V-MOS, Analog-S, 50V, 0,2A, 0,6W, 20Ω	7d	-	
2 SK 636	MOS-N-FET-e	V-MOS, S-L, 500V, 8A, 80W, <1,4Ω	16c(p)	IRFPC 50	16p